

# SB80

## 60 Watt Six Drivers with Two Tweeter Soundbar and 80 Watt 8" Wireless Woofer

### Welcome to the Soundbar SB80 by Current Audio

The SB80 SoundBar describes the latest digital technology in amplified speaker sound bars with a powerful wireless amplified MegaBass subwoofer by Current Audio. The powerful subwoofer can be located anywhere in the room. This is the perfect Home Theater System with a wide sound stage. The system comes with a handheld remote to control power, switch inputs and adjust sound fields. You may also use the touch screen buttons on the SoundBar. The slim depth and sleek design blends with all flat LED/LCD TV models.

### Features and Connections for SoundBar

#### Rear Panel SoundBar

1. Power Switch-Rear panel switch to cut power for service or hook-up.
2. Input Power Jack-Connect the 12VDC power supply here.
3. Line Inputs-Three input methods are provided on the back panel. Digital Optical or Coaxial or standard analog RCA input from TV.
4. AUX IN-A standard 3.5mm audio jack for MP3, computers or mobile devices.
5. FM Antenna-Connect the supplied FM antenna to play FM radio.

#### Front and Side Panel SoundBar

6. Remote Control Receive Window-Aim the Remote to this area to control or change the functions of the system.
7. LCD Display-The Digital read out gives status of the system functions and will automatically dim after 60 seconds. Press any button on the remote to turn the display on.
8. Sound Source Touch Button-Switches between FM radio, Aux, USB, SD card, TV, Optical or Coaxial modes.
9. Volume Up/Down Touch Buttons-Manually control volume.
10. Power Touch Button-Place system in Standby OFF mode or ON mode.
11. USB-Port-2.0 Input for MP3 or WMA format music files.
12. SD Memory Card Port-Input for MP3 and WMA format music files.
13. Mounts-packed with each amp is an accessory pack that include brackets allowing the SoundBar to be table top or wall mounted.

#### Subwoofer

14. Input power Jack-Connect 110VAC 2 conductor power cord here.
15. Power Mode-Power ON or OFF
16. Match Button and Status LED-Used to sync the SoundBar with the MegaBass for control of the subwoofer.



### SPECIFICATIONS

Soundbar Power	60 Watts RMS Ported
Subwoofer Power	80 Watts RMS Powered
Sound Mode	Selectable 2.0/2.1 with Enhanced DSP Surround Modes
Speakers	8 Speakers. 6 2.5" Midrange Drivers and 2 1.25" Tweeters
Subwoofer	2.4GHz 8" Long Throw Ported Woofer
Bluetooth	Connectivity for iPhone, Android, MP3 and PC
Audio Inputs	Digital Optical, Digital Coaxial, RCA, 3.5mm
USB and SD Memory Slot	MP3, USB HD, PC, Mobile Phone
Frequency Response	20 Hz to 20 kHz
FM Tuner	Built-in FM Tuner
Soundbar Dimensions (weight)	39 3/4" (1010mm) x 3 1/2" (89mm) x 3 5/16" (84mm) 9lbs.
Subwoofer Dimensions (weight)	17 1/8" (435mm) x 8 11/16" (221mm) x 14 1/4" (362mm) 21 lbs



Part Number 93104

Manual URL [www.currentaudio.com](http://www.currentaudio.com)

